

# DIGITAL RECEIVER

## Digital Satellite Receiver DRS 100 CI

- Power consumption Stand by 0.5 W
- 12 V connection
- Supersmall dimensions for positioning e.g. behind the TV set
- SAT Mouse with integrated IR receiver and Operating LED
- Common Interface for the connection of modules for encrypted TV channels
- Home Cinema connector (optical AC-3 output)
- Hotel mode (lock of the installation menu, setting of max. volume)
- Blind Scan – Symbol rate is detected automatically
- Program Service Plus – Display of existing add-on services
- Channel selection either numerical or alphanumerical
- 3000 TV channels and 1500 radio stations storeable
- Integrated teletext decoder with 1000 pages memory
- High ease of use
- Short zapping times



### DRS 100 CI

No. of channels TV/Radio	3000/1500
No. of SAT positions	max. 16
Frequency range	950 – 2150 MHz
Input symbol rate	1 – 45 Msymb/s
SAT IF input	F-connector
LNC supply	13/18 V, max. 300 mA
LNC switching signal	0/22 kHz, 0.5 V <sub>ss</sub> Toneburst
DiSEqC-version	1.0
Search modes	automatically/manually
Last station memory	yes
Teletext	Internal teletext decoder with 1000 pages memory and via TV set
Software Download	Via ASTRA satellite 19.2° east
Wall power supply	230 V/12–24 V
Power consumption	max. 14 W in operation, 0.5 W in Stand by mode
Dimensions (W x H x D)	219 x 53.5 x 119 mm
Weight	approx. 1.0 kg